

# LUXORliving J4-6

Item no.: 4800451

theben

Home and Building control  
LUXORliving

## Description

- 4-way LUXORliving blind actuator
- with integrated inputs for the push buttons, as a replacement for drive control of the LUXOR living comfort control
- Allows an easy system change for existing LUXOR customers to LUXORliving
- For controlling drives for blinds, roller blinds, as well as sun and vision protection devices
- Manual operation on the device (even without bus voltage)
- LED Up and Down switching status indicator for each channel
- Features: 8 relay outputs for 4 drives (Up/Down), 4 inputs for individual operation of the drives (230 V), 2 inputs for central and group operation (230 V)
- The relay outputs are not floating or potential-independent, but are powered by the supply voltage
- This means that all drives connected to the actuator are controlled via the same phase. This has to be considered when changing from LUXOR to LUXORliving
- Download of the installation software LUXORplug at <https://luxorliving.de/luxorplug>




## Technical data

LUXORliving J4-6	
Operating voltage KNX	<10 mA
Operating voltage	230 V AC
Stand-by consumption	<0.2 W
Number of channels	4
Width	4 modules
Installation type	DIN rail

LUXORliving J4-6	
Output	NO contact, 6 A
Switching output	Potential-free, for SELV, if the whole device switches SELV
Type of protection	IP 20
Protection class	II according to EN 60 669

## Connection example



Subject to technical changes and misprints

additional information at: [www.theben.de/product/4800451](http://www.theben.de/product/4800451)

The load data are determined with exemplary selected illuminants and are therefore typical data due to the large number of available products.

## Scale drawings

